

# Compact Wireless Mono Laser All-in-One Printer with Fax and Double-sided Printing

## TIME SAVING

26ppm copy and print speeds  
Less refilling with a 35 sheet Automatic Document Feeder and 250 sheet paper Tray

## QUALITY

High resolution colour network scanning plus scan to PDF feature

## FLEXIBILITY

Fast Wi-Fi connection with the latest security or connect to your network via the built-in Ethernet, or to your PC with Hi-Speed USB 2.0

## PEACE OF MIND

With free 12-month warranty and lifetime technical support



## HI-SPEED

First page out time of less than 8.5 seconds  
Hi-Speed faxing with up to 200 speed dial locations

## SPACE SAVING

Compact footprint makes this ideal for a small office where space is at a premium

## LOWER RUNNING COSTS

Save paper with double-sided printing as standard  
Separate drum and toner to help keep costs down – only replace the one that's run out  
1,200 page toner in the box  
Reduce cost with longer lasting high yield toners

MFC-7860DW

## GREEN AND CLEAN TECHNOLOGY

That meets environmental standards



Not only does this clever machine give you the flexibility of wired or wireless connectivity, it also frees up space in a small office with 26 pages per minute printing and copying, plus faxing and colour network scanning all in one machine. The automatic document feeder and 250-sheet paper tray leave you free to do other things instead of waiting for your documents; and with double-sided printing cutting paper costs and a 1200-page toner as standard to reduce running costs, you'll even free up some of your office budget too!

# MFC-7860DW

## Technical specifications

### General

**Engine:** Electrophotographic laser  
**Processor:** ARM946E-S 200MHz  
**Local Interface:** Hi-Speed USB 2.0  
**Wireless Network Interface:** IEEE802.11b/g (Infrastructure Mode / Adhoc Mode)  
**Wired Network Interface:** Built in 10/100 Base-TX Network  
**Wireless Setup Utilities:** Wi-Fi® Protected Setup (WPS) & AirStation One-Touch Secure System (AOSS)  
**Wireless Support:** Intel My Wi-Fi® Technology (vertical pairing). This is a method of easily connecting the Brother MFC-7860DW to any Intel My Wi-Fi® Technology supported device  
**LCD Display Size:** White backlight 2 lines x 16 characters  
**Memory Capacity:** 32MB (RAM)  
**On / Off Switch:** Yes

### Mono Printer

**Simplex Print Speed:** Up to 26ppm (pages per minute)  
**Duplex Print Speed:** Up to 5ppm (pages per minute)  
**Resolution:** HQ1200 (2,400 x 600 dpi) quality  
**First Print Out Time [From Ready Mode]:** Less than 8.5 seconds  
**Warm Up Time [From Sleep Mode]:** Less than 7 seconds  
**Emulation:** PCL6 & BR-Script 3 (PostScript® 3 Language Emulation)  
**PCL Resident Fonts:** 66 scalable fonts, 12 bitmap fonts, 13 bar codes  
**BR-Script 3:** 66 Fonts

### Mono Copier

**Speed:** Up to 26cpm (copies per minute)  
**First Copy Out Time [From Ready Mode]:** Less than 11 seconds  
**Resolution:** 600 x 600 dpi  
**Multi-Copying / Stack / Sort:** Makes up to 99 copies of each page / Stacks or Sorts  
**Enlargement / Reduction Ratio:** Easily copy documents to a required paper size (25% to 400% in 1% increments).  
**Save Paper:** Copy 2 or 4 pages to a single page (N-up copying)

### Colour Scanner

**Resolution (Optical):** Up to 600 x 2,400 dpi  
**Resolution (Interpolated):** Up to 19,200 x 19,200 dpi  
**Colour Depth:** 48bit internal / 24bit external colour scanner  
**Grey Scale:** 256 shades of grey are available for faxing, copying or scanning  
**TIWAIN Scanner Compliance:** Windows® 7, Windows Vista®, Windows® XP, Windows® 2000 and OS X 10.3.9 or greater  
**WIA Scanner Compliance:** Windows® 7, Windows Vista®, Windows® XP  
**SANE Scanner Compliance:** Linux  
**Scan To:** E-mail, image, OCR, file (Requires the Brother Control Centre software)  
**Scan To:** FTP (File Transfer Protocol)  
**Scan To:** E-mail Server\*\*\*, Internet Fax (I-Fax) \*\*\*  
**Scan Key:** Enables user to scan a document to e-mail, image, OCR, file (Requires the Brother Control Centre software) FTP, e-mail server\*\*\*

### Mono Fax

**Modem Speed:** 33, 6kbps  
**Internet Fax:** Save money by sending & receiving faxes over the Internet\*\*\*  
**Transmission Speed:** Approx. 2.5sec. Up to 500 pages (ITU-T Test Chart, Standard Resolution, JBIG)  
**ITU-T group compatibility:** Super G3  
**Data Compression:** MH / MR / MMR / JBIG / JPEG  
**Backup for clock:** Up to 60hrs  
**Memory Backup:** Yes  
**Automatic Redial:** Automatic redialling if the recipient fax is busy  
**One-Touch Dials:** 8 locations (auto dialling of a pre-stored number performed by the touch of one key)  
**Speed Dials:** 200 locations (auto dialling of pre-stored number by entry of a three digit number)  
**Group Dial:** A combination of up to 8 one-touch & speed dial numbers can be stored on a one-touch key for broadcasting  
**Telephone Index:** An electronic, alphabetical listing of stored one-touch, speed dial and group numbers  
**Chain Dialling:** Allows the user to store parts for long dialling sequences in different one-touch or speed dial locations  
**Station ID:** This is the stored information that appears on the top of faxed pages  
**FAX / TEL Switch:** Automatic recognition of fax and telephone reception  
**Distinctive Ring Detection:** A service purchased from a telephone company that allows two or more telephone numbers to share a single fixed line, the function enables the machine to provide a different ring tone for each number. (UK and Denmark)  
**Speaker / Ring volume:** 3 steps and off  
**Grey Scale:** 8 bit / 256 levels  
**Contrast:** This allows the user to change the contrast between auto / light / dark  
**Delayed Timer:** Up to 50  
**Polling:** This feature enables a machine to request another machine to send information on demand  
**Quick-Scan (Memory Transmission):** Reduce scanning times by scanning a fax into memory before sending (Approx. 2.5 sec./page (A4/Letter Standard Resolution)).  
**Out of Paper Reception:** Up to 500 pages (ITU-T Test Chart, Standard Resolution, JBIG)  
**Broadcasting:** Send the same fax message to up to 258 separate locations (groups, one-touch, speed-dial numbers and up to 50 manually dialled numbers)  
**Batch Transmission:** Stores documents for the same location in the machines memory for transmission in a single call  
**Auto Reduction:** When receiving a single page document between 297mm and 350mm long the fax machine will automatically reduce the message to fit onto a single A4 sheet  
**ECM (Error Correction Mode):** Where machines share the ECM feature, it will detect line errors during fax transmission and resend the page(s) of the document that had an error  
**Dual Access:** Allows the user to dial a number, and begin scanning the fax into memory, even when the MFC is receiving, sending or printing a fax from memory.  
**Fax Forwarding:** Sends a fax received in memory to another pre-programmed fax number  
**PC Fax Send & Receive:** Sends & receives faxes direct from / to your PC from network or USB. (Send only for Mac & Linux)  
**Remote Access:** Allows the user to remotely access their machine by using another touch tone phone

### Printer Driver

**Windows®:** Windows 7® (32 & 64 bit editions), Windows Vista® (32 & 64 bit editions), Windows XP Home Edition, Windows XP Professional (32 & 64 bit editions), Windows® Server 2008R2, Windows® Server 2008 (32 & 64 bit editions), Windows® Server 2003 (32 & 64 bit editions), Windows® 2000 Professional, Windows® Terminal Services 2003 & 2008, Citrix Presentation Server®, Citrix XenApp®, Citrix XenDesktop®  
**Apple Macintosh:** Mac OS X 10.4.11 or greater  
**Linux\*\*\*:** CUPS printing system(x86, x64 environment), Linux printer driver for LPD/LPRng printing system (x86, x64 environment)

### Printer Driver Installation Options

**Installation Wizard:** An easy to use wizard that will guide you through whole installation process  
**Printer Driver Only:** Install only the printer driver using your own installation method  
**Unattended Installer:** An effective way to automatically deploy printer drivers over a network to multiple Windows® computers  
**Driver Deployment Wizard [DDW]:** Guides you through the printer driver install and creates an executable file that can be used to install the printer driver on other PC's (Windows® only).  
**Wireless Installer Wizard:** Step by step guide, manageable through the control panel or device driver software, for connecting the Brother MFC-7860DW to your wireless network

### Printer Driver Functions

**N-up Printing (Windows® & Mac only):** Reduce up to 2, 4, 9, 16 or 25 A4 pages into just one A4 page  
**Poster Printing†:** Enlarge 1 A4 page into a poster using 4, 9, 16 or 25 A4 pages  
**Watermark Printing†:** Watermark your documents with predefined text or with your own user-defined messages  
**Automatic Duplex†:** Automatically print to both sides of a piece of paper  
**Booklet Printing†:** Print documents in A5 Booklet format using automatic duplex

### Security

**Secure Print †:** Protect your print jobs with a pin number, enter the pin number at the machine to print the documents  
**Secure Function Lock 2:** Restrict the different functions (print, copy, scan & fax) and configure print page limits

### Remote Network Management Utilities

**Web Based Management:** Apply configurations, check settings and view usage information through a web browser  
**BRAdmin Light:** For setup and LAN management (up to 15 devices)  
**BRAdmin Professional\*\*\*:** For LAN / WAN management (for more than 15 devices)  
**Web BRAdmin\*\*\*:** For LAN/WAN management accessible through a web browser (Server based management utility for your printer fleet / Windows® IIS(4.0/5.0) mode only)  
**E-mail reports:** Reports containing basic usage data sent to a nominated e-mail address on a cyclical basis  
**E-mail notifications:** Alerts sent to a nominated e-mail address when anything which can disrupt printing activity occurs

### Network Protocols & Security

**TCP/IP:** IPv4 and IPv6  
**IPv4:** ARP, RARP, BOOTP, DHCP, APIPA(Auto IP), WINS/NetBIOS name resolution, DNS resolver, mDNS, LLNMR responder, LPR/LPD, Custom Raw Port/Port 9100, IPP, FTP Server, SNMPv1/v2c, HTTP Server, TFTP Client and Server, SMTP Client, ICMP, LLTD responder, Web Services (Print)  
**IPv6 (Off by default):** NDP, RA, DNS Resolver, mDNS, LLNMR responder, LPR/LPD, Custom Raw Port/ Port 9100, IPP, FTP Server, SNMPv1/v2c, HTTP Server, TFTP Client and Server, SMTP Client, ICMPv6, LLTD responder, Web Services (Print)  
**Wired Network Security:** APOP, POP before SMTP, SMTP-AUTH  
**Wireless Network Security:** WEP 64/128 bit, WPA-PSK (TKIP/AES), WPA2-PSK (AES), APOP, POP before SMTP, SMTP-AUTH

### Paper Handling

**Paper Input\*\*:** Standard Tray: 250 sheets  
Manual paper feed slot: 1 sheet  
ADF (Automatic Document Feeder): Up to 35 sheets  
**Paper Output\*\*:** Face Down (standard output): 100 sheets  
Face Up: 1 sheet (straight paper path) 1 sheet

### Media Specifications

**Media Types:** Standard Tray Plain paper, thin paper, recycled paper  
Manual paper feed slot: Plain paper, thin paper, thick paper, recycled paper, bond paper, labels and envelopes  
**Media Weights:** Standard Tray: 60 – 105g/m²  
Multi-Purpose Tray: 60 – 163g/m²  
**Media Sizes:** Standard Tray: A4, letter, B5(ISO/JIS), A5, A5 (long edge), B6(ISO), A6, executive  
Multi-Purpose Tray: Width (76.2 – 220mm) x length (116.0 x 406.4)  
**List / Report:** System Set-up List - A printed report that shows the current setting of your machine.

### Page Counters - Available to view in LCD & printed report, web based management & BRAdmin

**Total Print Pages:** Informs the user of the total number of all pages produced from this machine  
**Copy Pages:** Informs the user of the total number of copies made on this machine in pages  
**PC Print Pages:** Informs the user of the total number of PC prints from this machine  
**Report Pages:** Informs the user of the total number of reports printed on this machine in pages

### Supplies

**Standard Toner:** (TN-2210) 1,200 pages\*  
**High yield toner:** (TN-2220) 2,600 pages\*  
**Drum:** (DR-2200) 12,000 pages

\*The frequency of replacement of consumables will vary depending on the complexity of the prints, the percentage of coverage, paper size, page per job, and the type of media.

### Dimensions & Weights

**With carton & consumables:** 527 (W) x 510 (D) x 493 (H) mm, 14.8Kg  
**Without carton, with consumables:** 405 (W) x 398.5 (D) x 316 (H) mm, 11.6Kg

### Power Consumption

**Printing:** Average 445W at 25c  
**Ready:** Average 55W at 25c  
**Sleep (WLAN On):** Average 3.9w at 25c  
**Deep Sleep (WLAN Off):** Average 1.7w at 25c

### Sound Pressure Level

**Printing:** Less than 53 dB  
**Ready:** Less than 30 dB

### Sound Power Level

**Printing:** Less than 6.40B  
**Ready:** Less than 4.22B

### Ecology

**Typical Electrical Consumption (TEC):** 1.339 kWh / week  
**Power Saving:** This enables the machine to consume less energy when not in use.  
**Toner Saving:** This reduces the toner usage and helps to reduce the total cost of printer ownership.  
**Energy Star:** Certified to the world-wide eco label for power consumption.

### Duty Cycles

**Recommended:** 250 – 2,000 pages monthly print volume  
**Maximum:** 10,000 pages monthly print volume

### Contents

**Toner cartridge:** up to 1,200 pages\*  
**Drum unit:** up to 12,000 pages  
**Power:** supply cord  
**Telephone:** line cord  
**Driver software:** for Windows® & Apple Macintosh  
**User Guide:** (CD-ROM)  
Quick Set-up Guide  
**PC interface:** cable NOT included

† For Windows only

†† Requires the Brother Control Centre Software

††† For USB printing only.

\*Approx. yield is declared in accordance with ISO/IEC 19752

\*\*Calculated with 80g/m² paper

\*\*\* Downloaded free of charge from Brother's Solutions Centre <http://solutions.brother.com>

**brother**  
at your side

Brother UK Ltd, Audenshaw, Manchester M34 5JD  
Tel: +44(0)8444 999 444 Fax: +44(0)161 931 2218  
Web: [www.brother.co.uk](http://www.brother.co.uk)