# HP LaserJet Pro 4001-4004ne/dne/dwe HP+ Printer series



Get blazing fast speeds and a smart printing system for effortless, secure, and sustainable printing.

LaserJet Pro with HP+ works exclusively with an HP account, internet connection, and use of only Original HP Toner for the life of the printer. Get blazing fast speeds and a smart printing system for effortless, secure, and sustainable printing.



#### HP LaserJet Pro 4001ne Printer



HP LaserJet Pro 4001dne Printer



HP LaserJet Pro 4001dwe Printer

## Maximum productivity.

- Support your dynamic workteam with this high-performing printer, ideal for up to 10
- Step up your workflow with blazing fast speed to meet high-demand environments.
- Get productivity in the palm of your hand. Print and save time with Shortcuts from HP Smart. 1
- Don't wait for print jobs. With no warm-up time, your printer is always ready.

## Effortless management.

- Guided, cloud-based setup makes it easy to configure new printers and onboard users from any location.<sup>2</sup>
- Smart Admin Dashboard monitors usage and control settings across multiple printers, in multiple locations.<sup>2</sup>
- Seamless connectivity allows you to print from anywhere, any device, on any network. 1,3
- Dedicated tech support can help you when you need it, all backed by our 2-year extended HP warranty.

## HP Wolf Pro security, made better with HP+.

- Get printer security out of the box. Preconfigured settings mean it's ready when you are.
- Set up your printer security from the dashboard. Smart Admin makes IT configuration and monitoring easy. 2
- Automated 24/7 monitoring helps ensure your printers and your information are always
- Add a layer of security. PIN/pull option authenticates your print jobs only when you're

## Hassle-free supplies management with Instant Ink.

- Enroll to save on Original HP Toner with Instant Ink. Get toner, delivery, and recycling.
- Never run out of toner with Instant Ink for laser. 11
- With Instant Ink, get toner automatically delivered to workers or offices all on one consolidated bill.
- With Instant Ink, you get to select the right plans for each of your printers. Change or cancel at any time. 12

app (Smart Pro): Requires the HP Smart app download. For details on local printing requirements see www.hp.com/go/mobileprinting. Certain features/software are available in English language only and differ between desktop and mobile applications

<sup>15</sup>mart app (Smart Pro): Requires the HP Smart app download. For details on local printing requirements see www.hp.com/go/mobileprinting. Certain features/software are available in English language only and differ between desktop and mobile applications. Subscription may be required.

2Easy to set up and manage - Requires use of Smart Admin Dashboard for printer setup and onboarding of users.

3Connected and ready - HP+ printers are ready when you are with improved connectivity utilizing Smart Driver and Print/Scan Doctor technology.

4Dedicated support - speak with a live HP+ support representative Monday through Friday Ban to 10 pm ETS Tasturday and Sunday 9am to 8 pm EST. Excludes public holidays.

5Extended warranty; 2/yrs HP Warranty in total. Refer to the documentation in the printer box for further information on HP warranty.

6Wireless operations are compatible with 2.4 GHz and 5.0 GHz operations only. Learn more at hp.com/go/fosecuritymanager.

7HP JetAdvantage Security Manager must be purchased separately. To learn more, please wish the com/go/securitymanager.

8Save up to 50% on toner (mono) — Based on monthly subscription cost of HP Instant Ink monochrome toner cartridge printers < \$493 USD and < £6494 and MPPs priced < \$649 USD and < £649 USD and <

# Product walkaround

# Series at a glance







Model	HP LaserJet Pro 4001ne Printer	HP LaserJet Pro 4001dne Printer	HP LaserJet Pro 4001dwe Printer

### **HP Services**

Downtime can have serious consequences, so HP provides support beyond the standard warranty. You benefit from reduced risk, maximized uptime, predictable service delivery and no unbudgeted repair costs. HP Care Pack Services provide a comprehensive suite of protection services designed to keep HP hardware and software up and running so employees can stay productive.

For carepack availability visit: hp.com/go/cpc

#### Top features

Compact design with groundbreaking performance. High-speed, double-sided printing at up to 42 ppm and self-healing Wi-Fi®. HP Smart enabled so you can easily print from anywhere, including applications like Google Drive™ and Dropbox™

Set up and manage your LaserJet Pro from a single dashboard. Onboard users, track toner levels, monitor security and control settings from any location. Get the help you need with dedicated tech support, all backed by our 2-year extended warranty.

Advanced 24/7 security monitoring with legendary HP Wolf Pro Security comes out of the box embedded and preconfigured. Smart Security alerts you to potential security risks with your settings

Save on toner and never run out when you subscribe to Instant Ink for laser—an automatic toner subscription that delivers toner only when you need it. That way, you can focus on running your business. Get 3 months of toner included when you enroll. 8,9,111

#### Supplies

W1480A W1480X HP 148A Black Original LaserJet Toner Cartridge HP 148X High Yield Black Original LaserJet Toner Cartridge

#### Solutions

Security: HP Security Manager; Smart Security; HP Secure Print and Insights

Mobile and universal print: HP Universal Print Driver (UPD): HP Roam for Business: Optional ROAM Queue Printing: HP Print for Chrome Extension: Print Anywhere with Private Pickup; HP Smart Printing Driver; HP Smart UPD; HP Smart App

Management: HP Web JetAdmin; HP Smart Device Services (SDS); Embedded Web Server; HP Smart Admin; HP Smart Printer Administrator's Resource Kit; HP Command Center 2.0(ECP); Premium Fleet & Security Management on ECP(Premium Experience)

#### Services

U42H0E - HP 3 year Next Business Day Service for LaserJet Pro 400xe

U42H1E - HP 4 year Next Business Day Service for LaserJet Pro 400xe

U42H2E - HP 5 year Next Business Day Service for LaserJet Pro 400xe

U42H3E - HP 3 year 4 hour 9x5 Service for LaserJet Pro 400xe

U42H4E - HP 4 year 4 hour 9x5 Service for LaserJet Pro 400xe

U42H5E - HP 5 year 4 hour 9x5 Service for LaserJet Pro 400xe U42H6E - HP 3 year Next Business Day Advanced Exchange Service for LaserJet Pro 400xe

U42H7E - HP 3 year Return to Depot Service for LaserJet Pro 400xe

**U42H8PE** - HP 1 year Post Warranty Next Business Day Service for LaserJet Pro 400xe

**U42H9PE** - HP 1 year Post Warranty 4 hour 9x5 Service for LaserJet Pro 400xe

**U42HBPE** - HP 1 year Post Warranty Next Business Day Advanced Exchange Service for LaserJet Pro 400xe

U42HCPE - HP 1 year Post Warranty Return to Depot Service for LaserJet Pro 400xe U9JT1E - HP Installation with Networking Service for Personal Scanner and Printing

art app (Smart Pro): Requires the HP Smart app download. For details on local printing requirements see www.hp.com/go/mobileprinting. Certain features/software are available in English language only and differ between desktop and mobile applications

Smart app (Smart Pro): Requires the HP Smart app download. For details on local printing requirements see www.hp.com/go/mobileprinting. Certain features/software are available in English language only and differ between desktop and mobile applications. Subscription may be required.

Easy to set up and manage – Requires use of Smart Admin Dashboard for printer setup and onboarding of users.

Connected and ready – HP+ printers are ready when you are with improved connectivity utilizing Smart Driver and Print/Scan Doctor technology.

Dedicated support - speak with a live HP+ support representative Monday through Friday Baan to 10 pm ETS T Saturday and Sunday 9am to 8 pm EST. Excludes public holidays.

Extended warranty. 2yrs HP Warranty in total. Refer to the documentation in the printer box for further information on HP warranty.

Melicated support - speak with a live HP+ support representative Monday further information on HP warranty.

Melicated support - speak with a live HP+ support representation are comparable with 2.4 GHz and 5.0 GHz to perations on soly, Learn more at hp.com/go/Securitymanager.

Ple JetAdvantage Security Manager must be purchased separately. To learn more, please visit hp.com/go/Securitymanager.

Place of Ple HP Instant like. Sale prices not considered for this study. Printers which only use XL cartridges printers service 1,500-page plan without purchase of additional sets of pages compared to cost per page to print ISO/IEC 24711 pages on most in-class, traditional A4 monochrome toner cartridge printers < 493 USD and < 6494 and MPPs priced < 5649 USD and < 6672 using original standard-capacity integrated cartridges (toner and drum in one cartridge). Average (PP per country used to determine percent savings claim versus CPP for HP Instant like. Sale prices not considered for this study. Printers which only use XL cartridges standard-capacity integrated cartridges (toner and drum in one cartridge). Average (PP per country used to determine percent savings claim versus CPP for HP Instant lik

# HP LaserJet Pro 4001-4004ne/dne/dwe HP+ Printer series

Model	HP LaserJet Pro 4001ne Printer	HP LaserJet Pro 4001dne Printer	HP LaserJet Pro 4001dwe Printer		
Product number	2Z599E	2Z600E	2Z601E		
AIO functions	Print				
Print					
Print speed <sup>7,9,8</sup>	First page out Letter: As fast as 6.1 sec Black; First page out A4: As fast as 6.3 sec Black; Letter: Up to 42 ppm Black; A4: Up to 40 ppm Black; Print speed (Landscape, A5): Up to 63 ppm Black				
Print resolution	Black (best) Fine Lines (1200 x 1200 dpi); Black (normal) Normal (Native: 600 x 600 dpi, enhanced up to 4800 x 600 dpi); Black (fine lines) Fine Lines (1200 x 1200 dpi)				
Print technology	Laser; Print resolution technology: HP FastRes1200, HP ProRes1200, Economode				
Print cartridges number	1 (black)				
Standard print languages	HP PCL 6, HP PCL 5e, HP postscript level 3 emulation, PDF, URF, PWG Raster				
Printer smart software features	Manual duplex and booklet printing, HP Auto-On/Auto-Off Technology, Job Storage with PIN printing, N-up printing, collation, watermarks, install printer driver only, Economode for toner savings, accepts a variety of paper sizes and types	Auto duplex and booklet printing, HP Auto-On/Auto-Off Technology, Job Storage with PIN printing, N-up printing, collation, watermarks, install printer driver only, Economode for toner savings, accepts a variety of paper sizes and types			
Printer management / HP SureSupply	HP Printer Assistant; HP Web JetAdmin Software; HP JetAdvantage Security Manager; HP SNMP Proxy Agent (Part of HP WebJetAdmin); HP WS Pro Proxy Agent (Part of HP WebJetAdmin); Printer Administrator Resource Kit for HP Universal Print Driver (Driver Configuration Utility - Driver Deployment Utility - Managed Printing Administrator)/				
Connectivity					
Standard connectivity	1 Hi-Speed USB 2.0; 1 host USB at rear side; Gigabit Ethernet 10/100/1000BASE-T network; 802.3az(EEE)		1 Hi-Speed USB 2.0; 1 host USB at rear side; Gigabit Ethernet 10/100/1000BASE-T network; 802.3az(EEE) 802.11b/g/n / 2.4 / 5 GHZ Wi-Fi radio + Bluetooth		
Mobile printing capability	HP Smart App; Apple AirPrint™; Mopria™ Certified		HP Smart App; Apple AirPrint™; Mopria™ Certified; Wi-Fi® Direct printing; HP ROAM For Business; Optional ROAM Queue Printing		
Memory	Standard: 256 MB; Maximum: 256 MB				
Processor speed	1200 MHz / Storage: Optional Job storage via external rear host USB port (Minimum 16 GB) / Hard disk: None				
Duty cycle (monthly)	Letter: Up to 80,000 pages; A4: Up to 80,000 pages; Recommended monthly page volume: 750 to 4,000				

# HP LaserJet Pro 4001-4004ne/dne/dwe HP+ Printer series

Model	HP LaserJet Pro 4001ne Printer	HP LaserJet Pro 4001dne Printer	HP LaserJet Pro 4001dwe Printer			
Product number	2Z599E	2Z600E	2Z601E			
Paper handling						
Input	100-sheet multipurpose Tray 1, 250-sheet input Tray 2; Up to 350 sheets (Tray 1: up to 100 sheets; Tray 2: up to 250 sheets) Standard					
Output	Standard: 150-sheet output bin; Up to 150 sheets Standard					
Envelope feeder	No .					
Standard paper trays	2					
Media types	Paper (plain, EcoFFICIENT, light, heavy, bond, colored, letterhead, preprinted, prepunched, recycled, rough); envelopes; labels					
Media weight	Tray 1: 16 to 53 lb; Tray 2 and Optional 550-sheet Tray 3: 16 to 32 lb					
Media Sizes Custom	Tray 1: 3 x 5 to 8.5 x 14 in; Tray 2, optional Tray 3: 3.94 x 5.83 to 8.5 x 14 in					
Dimensions (w x d x h)	15 x 14.06 x 8.5 in; 381 x 357 x 216 mm; <b>Maximum</b> : 15 x 25 x 9.5 in; 381 x 634 x 241 mm					
Weight	#Intentionally Left Blank; 8.22 kg #Intentionally Left Blank; 8.56 kg					
What's in the box <sup>2</sup>	HP Black Original LaserJet Toner Cartridge (~2,900 Pages); Getting Started Guide; Support Flyer; Warranty Guide; Regulatory Flyer; Power cord; USB cable (AP & Wireless Only)					
Replacement cartridges <sup>6</sup>	HP 148A Black Original LaserJet Toner Cartridge (~2,900 pages), W1480A; HP 148X Black Original LaserJet Toner Cartridge (~9,500 pages), W1480X					
Warranty features	Two-year Bench/Depot Repair warranty. Warranty and support options vary by product, country and local legal requirements. Contact your Contractual Vendor or go to hp.com/support to learn about HP award winning service and support options in your region.					
Energy star certified	No	Yes				
Energy efficiency compliance <sup>1</sup>	IT ECO Declaration					
Display	2-line back lit LCD graphic display					
Software included	No software solutions are included in the Box only on http://hp.com; http://123.hp.com;					
Fonts and typefaces	84 scalable TrueType fonts					
Compatible operating systems	Windows 11; Windows 10; Windows 7; Windows Client OS; Android; iOS; macOS 10.15 Catalina; macOS 11 Big Sur; macOS 12 Monterey					
Compatible network operating systems	Windows Server; Citrix; UNIX; Novell					
Minimum system requirements	PC.2 GB available hard disk space; Internet connection or USB port Internet browser. For additional OS hardware requirements see microsoft.com;  Mac: 2 GB available hard drive space; Internet connection or USB port Internet browser. For additional OS hardware requirements see apple.com					
Power <sup>4</sup>	Power supply type: Internal (built-in) Power Supply; Power supply required: 110-volt input voltage: 110 to 127 VAC (+/- 10%), 50/60 Hz (+/- 2 Hz); 220-volt input voltage: 220 to 240 VAC (+/- 10%), 50/60 Hz (+/- 2 Hz); (Not dual voltage, product varies by part runber with # Option code identifies). Power consumption: 495 watts (active printing), 5.5 watts (ready), 0.5 watts (sleep), 0.5 (Auto Off/Wake on LAN, enabled at shipment), 0.05 watts (Auto-off/Wake). Os watts (sleep), 0.5 (Auto Off/Wake). Characteristic varieties (Energy Stars 2.0).					
Acoustics	Acoustic power emissions: 6.6 B(A)					
Operating environment	Operating temperature range: 50 to 91°F; Recommended operating temp 70% RH	Operating temperature range: 50 to 91°F; Recommended operating temperature: 63.5 to 77°F; Storage temperature range: 4 to 104°F; Operating humidity range: 10 to 80% RH; Recommended operating humidity range: 30 to 70% RH				

#### Data sheet | HP LaserJet Pro 4001-4004ne/dne/dwe HP+ Printer series

- 1 EPEAT® registered where applicable. EPEAT registration varies by country. See http://www.epeat.net for registration status by country.
  2 For yield information on the cartridge included with your printer, see http://www.hp.com/go/toneryield. Yield values measured in accordance with ISO/IEC 19752 and continuous printing. Actual yields vary considerably based on images printed and other factors.
  3 Job Storage feature requires a purchase of separate USB flash drive with a minimum of 16 GB capacity.
  4 Typical Electricity consumption (TEC) rating represents the typical electricity consumed by a product during 1 week, measured in kilowatt-hours (kWh).
  5 Power requirements are based on the country/region where the printer is sold. Do not convert operating voltages. This will damage the printer and void the product warranty. Energy Star value typically based on measurement of 115V device and 230V for Blue

- Power requirements are based on the contrayregion where the printer is soin. Do not convert operating voltages. This will darkage the printer and void the product warrainy, energy star value typically based on measurement of 11sV device and 230 for slide Angel.

  Declared yields based on ISO/IEC 19752 and continuous printing. Actual yields vary considerably based on images printed and other factors. For details see http://www.hp.com/go/foneryield

  Measured using ISO/IEC 24734, excludes first set of test documents. For more information see http://www.hp.com/go/printerclaims. Exact speed varies depending on the system configuration, software application, driver, and document complexity.

  Measured using ISO/IEC 24734 Feature Performance Test, excludes first set of test documents. For more information see http://www.hp.com/go/printerclaims. Exact speed varies depending on the system configuration, software application, driver, and document complexity.



