

# HP LaserJet Pro MFP M125 series



## Satisfy your everyday office needs.

This affordable HP LaserJet Pro MFP is easy to install and delivers crisp, clear documents. Print, copy and scan with one, compact device that fits neatly into small office spaces.



Print, copy, scan  
Print/copy up to 20 ppm  
128 MB RAM, 600 MHz processor  
1 Hi-Speed USB 2.0, Fast Ethernet 10/100Base-TX  
Up to 600 x 600 dpi (with HP FastRes 1200)



Auto On/Off  
Technology



Instant-on  
Technology



Multiple paper sizes



Wireless direct

### Extend your printing reach.

- Keep up with the pace of business: print and copy at high speeds of 20 ppm.
- Get a first page out in as fast as 9.5 sec.

### Print on your terms.

- Print from virtually anywhere – using your smartphone, tablet and PC – with Apple® AirPrint™.<sup>1</sup>
- Easily print from mobile devices – without a network – using wireless direct printing.<sup>2</sup>
- Connect your MFP directly to a PC or Netbook via the included Hi-Speed USB 2.0 port.

### Handle the essentials.

- Speed through document tasks and set the pace for success with an MFP that prints, copies and scans fast.
- Get started immediately with HP Smart Install – no CD needed.<sup>3</sup>
- Easily copy both sides of a two-sided ID or other small document onto the front of a single-page.<sup>4</sup>
- Control made easy – just start printing right away with the easy-to-use, intuitive control panel.<sup>4</sup>

# Technical specifications

<b>Print technology</b>	Laser
<b>Functions</b>	Print, copy, scan
<b>Print speed</b>	Up to 20 ppm ISO black (A4) Measured using ISO/IEC 24734, excludes first set of test documents. For more information see <a href="http://hp.com/products/1/ISO/MMDPP/index.html">hp.com/products/1/ISO/MMDPP/index.html</a> . Exact speed varies depending on the system configuration, software application, driver, and document complexity.
<b>Standard connectivity</b>	<b>CZ172A:</b> Hi-Speed USB 2.0 port; <b>CZ173A:</b> Hi-Speed USB 2.0 port; built-in Fast Ethernet 10/100Base-TX network port; Wireless 802.11b/g/n;
<b>Wireless capability</b>	<b>CZ172A:</b> No; <b>CZ173A:</b> Yes, built-in WiFi 802.11b/g/n;
<b>Mobile printing capability</b>	<b>CZ172A:</b> No; <b>CZ173A:</b> HP ePrint, Wireless direct printing, Apple AirPrint™;
<b>Network capabilities</b>	<b>CZ172A:</b> Not available; <b>CZ173A:</b> Via built-in 10/100 Base-TX networking;
<b>Supported network protocols</b>	<b>CZ172A:</b> Not available; <b>CZ173A:</b> Via built-in networking solution: TCP/IP, IPv4, IPv6, print: L3-Direct port 9100 Direct Mode, LPD (raw queue support only), Web Services Printing, discovery: SLP, Bonjour, Web Services Discovery; IP Config: IPv4 (BootP, DHCP, AutoIP, Manual), IPv6 (Stateless Link-Local and via Router, Stateless via DHCPv6); management: SNMPv1, HTTP;
<b>Media Handling</b>	<b>Input capacity:</b> Up to 150 sheets <b>Output capacity:</b> Up to 100 sheets, Up to 10 envelopes Maximum: Up to 100 sheets <b>Duplex printing:</b> Manual (driver support provided)
<b>First page out time</b>	As fast as 9.5 sec black (A4, ready)
<b>Monthly duty cycle</b>	Up to 8,000 pages (A4); Recommended monthly page volume: 250 to 2,000
<b>Print languages</b>	PCLm/PCLm5
<b>Print capabilities</b>	Direct print supported: <b>CZ172A:</b> USB printing; <b>CZ173A:</b> USB printing; Wireless direct printing;
<b>Print Area</b>	Print margins: Top: 2 mm; Bottom: 5 mm; Left: 3 mm; Right: 4 mm; Maximum print area: 209 x 349 mm
<b>Print resolution</b>	Up to 600 x 600 dpi black
<b>Memory</b>	128 MB
<b>Printer smart software features</b>	<b>CZ172A:</b> HP Smart Install, HP Auto-On/Auto-Off; <b>CZ173A:</b> Smart Install, HP Auto-On/Auto-Off, HP ePrint, Apple AirPrint™, Wireless direct printing, Embedded Web Server;
<b>Copier settings</b>	Number of copies; Lighter/Darker; Reduce/Enlarge; Optimise (draft, text, mixed, picture); Paper size; Maximum number of copies: Up to 99 copies; Copy resolution: Up to 400 x 600 dpi
<b>Copy speed</b>	Up to 20 cpm black (A4)
<b>Copier smart software features</b>	Up to 99 multiple copies; Reduce/Enlarge from 25% to 400%; Contrast (lighter/darker); Resolution (copy quality)
<b>Scanner specifications</b>	Scanner type: Flatbed; Scan technology: Contact Image Sensor (CIS); Scan input modes: Solution Center Lite (Windows Vista, Windows XP) or Device Stage (Windows 7, Windows 8); TWAIN-compliant or WIA-compliant software; Twain version: Version 1.9; Duplex ADF scanning: No; Scan size maximum (flatbed, ADF): 216 x 297 mm; Optical scan resolution: Up to 1200 dpi
<b>Scan speed</b>	Up to 7 ppm (black & white), up to 5 ppm (colour)
<b>Bit depth/ Greyscale levels</b>	24-bit/ 256
<b>Scannable area</b>	Maximum media size: 216 x 297 mm
<b>Digital sending</b>	Standard: Scan to Email by HP Software; Scan to application by HP Software; Scan to file by HP Software
<b>Scan file format</b>	Windows Scan Software supports file format: JPG, RAW (BMP), PDF, TIFF, PNG; Mac Scan Software supports file format: TIFF, PNG, JPEG, JPEG-2000, PDF, PDF-Searchable, RTF, TXT
<b>Printer management</b>	HP Device Toolbox; Status Alerts (default install)
<b>Security management</b>	Password-protected network embedded Web server; 802.11: WEP, WPA, WPA2; SNMPv1 community password change
<b>Control panel</b>	<b>CZ172A:</b> Dual digit numeric LED display; Buttons (Up, Down, Cancel, Setup, Copy, Power); 7 LED indicator lights (Ready, Attention, Toner, Copies, Darker/Lighter, Reduce/Enlarge, Power); <b>CZ173A:</b> 2-line LCD; buttons (Up, Down, OK, Cancel, Back, Setup, Number of Copy, Dark/Light, Mono copy, Copy Menu, ePrint, Wireless, Power); 4 LED indicator lights (Attention, Ready, Power, Wireless);

<b>What's in the box</b>	<b>CZ172A:</b> HP LaserJet Pro MFP M125a; Preinstalled introductory HP LaserJet Black Cartridge (~700 pages); Installation guide; Getting Started guide; User's Guide; Support flyer; Warranty guide; Printer software and documentation on CD; Power cord; <b>CZ173A:</b> HP LaserJet Pro MFP M125nw; Preinstalled introductory HP LaserJet Black Cartridge (~700 pages); Installation guide, Getting Started guide, User's Guide, Support flyer, Warranty guide; Printer software and documentation on CD; power cord; USB cable;
<b>Supplies</b>	<b>CF283A</b> HP 83A Black Original LaserJet Toner Cartridge 1,500 pages
<b>Software included</b>	Windows: HP Installer/Uninstaller, HP PCLm5 print driver, HP WIA Scan Driver, HP TWAIN Scan Driver, HP Scan, Status Alerts, HP Update, DXP; Mac: HP Installer/Uninstaller, HP PCLm5 Print Driver, HP Scan, HP Setup Assistant, HP Utility, HP Alerts, HP Firmware Updater
<b>Minimum system requirements</b>	Windows: Windows 8 (32-bit/64-bit), Windows 7 (32-bit/64-bit), Windows Vista (32-bit/64-bit); 200 MB available hard disk space required (CD and Web Package); 400 MB available hard disk space required (Box Spec for Smart Install); 512 MB RAM installed; CD-ROM/DVD or Internet; USB or Network port Mac: Mac OS X v10.6.8; PowerPC G4, G5, or Intel® Core™ Processor; 500 MB available hard disk space; CD-ROM/DVD-ROM or Internet; USB or Network port
<b>Compatible operating systems</b>	Full software installs supported on: Windows 8 (32-bit/64-bit), Windows 7 (32-bit/64-bit), Windows Vista (32-bit/64-bit); Driver only installs supported on: Windows Server 2012, Windows Server 2008 (32-bit/64-bit), Windows Server 2008 R2 (x64) (SP1), Windows Server 2008 (Standard Edition), Windows Server 2008 (Enterprise Edition), Windows Server 2003 (32-bit/64-bit) (SP1 or higher); Mac OS X v10.6.8 or higher; Linux: Please check Linux on-line support: <a href="http://hplipopensource.com/hplip-web/install.html">hplipopensource.com/hplip-web/install.html</a>
<b>Media weight</b>	Tray 1: 60 to 163 g/m <sup>2</sup>
<b>Media types</b>	Paper (plain, LaserJet), envelopes, transparencies, labels, postcards
<b>Media sizes</b>	A4; A5; Envelopes (ISO DL, C5, B5); Post cards (JIS single and double); Custom: 76 x 127 to 216 x 356 mm
<b>Printer dimensions (W x D x H)</b>	420 x 365 x 254 mm
<b>Package dimensions (W x D x H)</b>	497 x 332 x 350 mm
<b>Printer Weight</b>	8.0 kg
<b>Package weight</b>	10.3 kg
<b>Operating environment</b>	Temperature: 15 to 32.5°C, Humidity: 30 to 70% RH
<b>Storage</b>	Temperature: -20 to 60°C, Humidity: 10 to 90% RH
<b>Acoustics</b>	Acoustic power emissions: 6.1 B(A)
<b>Power</b>	Requirements: Input voltage: 220 to 240 VAC (+/- 12%), 50/60 Hz (+/- 3 Hz) Consumption: 465 watts (printing), 110 watts (copying), 2.2 watts (ready), 0.7 watts (sleep/auto-off), 0.2 watts (manual off) Typical Electricity Consumption (TEC) Number: 0.502 kWh/Week
<b>Certifications</b>	CISPR 22:2008/EN 55022:2010 - Class B, EN 61000-3-2:2006 +A1:2009 +A2:2009, EN 61000-3-3:2008, EN 55024:2010, FCC Title 47 CFR, Part 15 Class B/ICES-003, Issue 5, GB9254-2008, GB17625.1-2003, EMC Directive 2004/108/EC (Europe), other EMC approvals as required by individual countries.
<b>Safety certifications</b>	IEC 60950-1:2005 +A1 (International), EN 60950-1:2006 +A11:2009 +A1:2010 +A12:2011 (EU), IEC 60825-1:2007, GS License (Europe), EN 60825-1:2007 (Class 1 Laser/LED Device), Low Voltage Directive 2006/95/EC with CE Marking (Europe), other safety approvals as required by individual countries.
<b>ENERGY STAR</b>	Yes
<b>Country of origin</b>	Made in China
<b>Warranty</b>	<b>CZ172A:</b> One-year limited warranty. Warranty and support options vary by product, country and local legal requirements.; <b>CZ173A:</b> One-year limited warranty. Warranty may vary by country as required by law. Go to <a href="http://hp.com/support">hp.com/support</a> to learn about HP award winning service and support options in your region.;
<b>Service and support</b>	<b>UH757E</b> HP 3 year Care Pack w/Next Day Exchange for LaserJet Printers <b>UH761E</b> HP 3 year Care Pack w/Standard Exchange for LaserJet Printers. (UH757E: Only Austria, Baltics, Belgium, Denmark, Finland, France, Germany, Ireland, Italy, Netherlands, Norway, Portugal, Spain, Sweden, Switzerland, UK, Czech, Greece, Hungary, Poland, Slovakia. UH761E: All EMEA countries).

<sup>1</sup>Only available on the M125rwn. Supports OS X® Lion, OS X Mountain Lion and the following devices running iOS 4.2 or later: iPad® (all models), iPhone® (3GS or later) and iPod touch® (third generation or later). Works with HP's AirPrint-enabled printers and requires the printer be connected to the same network as your OS X or iOS device. Wireless performance is dependent on physical environment and distance from the access point. OS X, iPad, iPhone and iPod touch are trademarks of Apple® Inc., registered in the United States and other countries. AirPrint™ and the AirPrint logo are trademarks of Apple Inc.

<sup>2</sup>Only available on the M125rwn. An app or driver may be required to use HP wireless direct. For more information, see [hponconnected.com](http://hponconnected.com). Wireless performance is dependent on physical environment and distance from access point.

<sup>3</sup>HP Smart Install works with Microsoft® Windows® only.

<sup>4</sup>Only available on the M125rwn.



<http://www.hp.com/uk>

© Copyright 2014 Hewlett-Packard Development Company, L.P. The information contained herein is subject to change without notice. The only warranties for HP products and services are set forth in the express warranty statements accompanying such products and services. Nothing herein should be construed as constituting an additional warranty. HP shall not be liable for technical or editorial errors or omissions contained herein.

4AA5-3477EEE, 07/14

